

Linksys SPA942

Sumario

- 1 Configuración dunha IP estática
- 2 Ver a Configuración Avanzada
- 3 Obter información do estado do teléfono
- 4 Configuración do Panel do teléfono e do número de liñas
- 5 Configuración das Extensións do teléfono

Configuración dunha IP estática



1. Pulsar no botón **Setup**.
2. Pulsar o número **9** ou navegar ata o opción **Network**.
3. No apartado **1 WAN Connection Type**, pulsar no botón **Edit** e pulsar o botón **option** ata que apareza a opción **Static IP**. Logo pulsar **OK**.
4. Logo ir ao apartado **Non-DHCP IP Address**. Pulsar en **Edit**, e configurarlle a IP estática do teléfono. Empregar a tecla asterisco (*) en vez de (.). Por exemplo, a dirección IP 10.200.100.1 será escrita como 10*200*100*1. Logo pulsa en **OK**.
5. Ir ao apartado **9 Non-DHCP Subnet Mask**. Pulsar no botón **Edit**, entón introducir a máscara de subrede do teléfono. Pulsar o botón **OK**.
6. No apartado **10 Non-DHCP Default Route**. Pulsar o botón **Edit**, e introducir a porta de enlace por defecto do teléfono IP. Logo pulsar **OK**.
7. Ir ao apartado **11 Non-DHCP DNS 1**. Pulsar o botón **Edit**, e introducir o servidor DNS1 para o teléfono. Pulsar **OK**.
8. Se fose necesario, ir ao apartado **12 Non-DHCP DNS 2** para configurarlle o servidor DNS2.
9. Logo escoller a opción **Save** para grabar todo o configurado.
10. Por último, acceder ao apartado **12 Reboot** e reiniciar o Teléfono.

Unha vez configurada a IP do Teléfono SIP podemos entrar na súa web de configuración dende calquera navegador: <http://10.200.100.1>

Unha vez aí podemos cambiar, se queremos, a súa configuración web:

Info System Phone User

[Admin Login](#) [basic](#) | [advanced](#)
[Personal Directory](#) [Call History](#)

System Information

DHCP:	Static IP	Current IP:	10.200.100.1
Host Name:	SipuraSPA	Domain:	
Current Netmask:	255.255.0.0	Current Gateway:	10.200.0.254
Primary DNS:	10.0.0.36		
Secondary DNS:	10.0.0.35		


Product Information

Product Name:	SPA-942	Serial Number:	4LO00HB09177
Software Version:	6.1.3(a)	Hardware Version:	1.0.3(524f)
MAC Address:	000E08D456A7	Client Certificate:	Installed
Customization:	Open	Licenses:	None

Phone Status

Current Time:	6/1/2009 16:40:47	Elapsed Time:	08:45:22
Broadcast Pkts Sent:	0	Broadcast Bytes Sent:	0
Broadcast Pkts Recv:	40377	Broadcast Bytes Recv:	4092324
Broadcast Pkts Dropped:	0	Broadcast Bytes Dropped:	0
RTP Packets Sent:	4504	RTP Bytes Sent:	720640
RTP Packets Recv:	4470	RTP Bytes Recv:	715200
SIP Messages Sent:	554	SIP Bytes Sent:	243563
SIP Messages Recv:	553	SIP Bytes Recv:	298564
External IP:		Operational VLAN ID:	n/a

Se queremos ver a configuración avanzada para configurar completamente o teléfono hai que pulsar en "Admin login":





A Division of Cisco Systems, Inc.

Linksys Telephone Configuration

Info

System
SIP
Regional
Phone
Ext 1
Ext 2
Ext 3
Ext 4
User

[User Login](#) [basic](#) | [advanced](#)
[Personal Directory](#) [Call History](#)

System Information

DHCP:	Static IP	Current IP:	10.200.100.1
Host Name:	SipuraSPA	Domain:	
Current Netmask:	255.255.0.0	Current Gateway:	10.200.0.254
Primary DNS:	10.0.0.36		
Secondary DNS:	10.0.0.35		

Product Information

Product Name:	SPA-942	Serial Number:	4LO00HB09177
Software Version:	6.1.3(a)	Hardware Version:	1.0.3(524f)
MAC Address:	000E08D456A7	Client Certificate:	Installed
Customization:	Open	Licenses:	None

Phone Status

Current Time:	6/1/2009 16:50:00	Elapsed Time:	08:54:35
Broadcast Pkts Sent:	0	Broadcast Bytes Sent:	0
Broadcast Pkts Recv:	41014	Broadcast Bytes Recv:	4155669
Broadcast Pkts Dropped:	0	Broadcast Bytes Dropped:	0
RTP Packets Sent:	4504	RTP Bytes Sent:	720640
RTP Packets Recv:	4470	RTP Bytes Recv:	715200
SIP Messages Sent:	564	SIP Bytes Sent:	247813
SIP Messages Recv:	563	SIP Bytes Recv:	303954
External IP:		Operational VLAN ID:	n/a

Configuración do Panel do teléfono e do número de liñas

No apartado "Phone" poderemos configurar certos parámetros interesantes do teléfono:

- En "General" configuramos o nome do teléfono e o título ou imaxe que queremos apareza no seu panel.
- Cada liña do teléfono que nos interese debemos adxuditala a unha extensión; no noso caso empregaremos só unha liña das catro posibles, as outras poñerémolas en "Disabled".

LINKSYS®
A Division of Cisco Systems, Inc.

Linksys Telephone Configuration

InfoSystemSIPRegional**Phone**Ext 1Ext 2Ext 3Ext 4User

[User Login](#) basic | [advanced](#)
[Personal Directory](#) [Call History](#)

General

Station Name: InformaticaVoice Mail Number: 8000

Text Logo: Grupo%0ATraballo VoI

BMP Picture Download URL:

Select Logo: Text Logo ▼Select Background Picture: Text Logo ▼

Screen Saver Enable: no ▼Screen Saver Wait: 300

Screen Saver Icon: Background Picture ▼

Line Key 1

Extension: 1 ▼Short Name: \$USER

Line Key 2

Extension: Disabled ▼Short Name: \$USER

Line Key 3

Extension: Disabled ▼Short Name: \$USER

Line Key 4

Extension: Disabled ▼Short Name: \$USER

Line Key Extended Function

Subscribe Expires: 1800Subscribe Retry Interval: 30

Subscribe Delay: 1SPA932 Call Pickup Code: *98

SCA Line ID Mapping: Vertical First ▼ACD Ext: 1 ▼

Configuración das Extensións do teléfono

O SPA 942 ten catro liñas posibles pero só empregamos unha delas, que foi a que se enlazou á "Extensión 1" no apartado anterior, a configuración da Extensión faise tal e como se ve na seguinte imaxe:

LINKSYS®
A Division of Cisco Systems, Inc.

Linksys Telephone Configuration

Info	System	SIP	Regional	Phone	Ext 1	Ext 2	Ext 3	Ext 4	User	User Login	basic	advanced
										Personal Directory	Call History	

General

Line Enable:

yes

NAT Settings

NAT Mapping Enable:

no

NAT Keep Alive Enable:

no

SIP Settings

SIP Port:

5060

SIP Debug Option:

none

Call Feature Settings

Message Waiting:

no

Default Ring:

1

Mailbox ID:

Proxy and Registration

Proxy:

voip.iessandlemente.net

Register:

yes

Make Call Without Reg:

no

Register Expires:

3600

Ans Call Without Reg:

no

Subscriber Information

Display Name:

Informatica

User ID:

7000

Password:

Use Auth ID:

no

Auth ID:

Audio Configuration

Preferred Codec:

G711a

Use Pref Codec Only:

no

Second Preferred Codec:

G711u

Third Preferred Codec:

Unspecified

Silence Supp Enable:

no

DTMF Tx Method:

Auto

Undo All Changes

Submit All Changes

[User Login](#) [basic](#) | [advanced](#)

Copyright © 1992-2006 Cisco Systems, Inc. All Rights Reserved.